



Genuine products

Dedicated Support

Doorstep Delivery

ABB **ADD TO WISH LIST**

Share with your friends **eMart**



Automation & Control

TAL16-30-10 77-143V DC Contactor

₹1090.68 + ₹196.32 (GST 18%)

- 1 +

Buy Now

Add to Cart

Pin Code

Calculate Shipping

Please enter your PIN Code to check the best offers

Product Id#: 1SBL183061R6210

[Be the first to review this product](#)

Sold and delivered by **Micronova Impex Pvt Ltd**

TAL16 contactors are mainly used for controlling 3-phase motors and generally for controlling power circuits up to 690 V AC or 220 V DC. The contactors can also be used for many other applications such as isolation, capacitor switching, lighting. The TAL... series 1-stack 3-pole contactors are of the block type design. - Main poles and auxiliary contact blocks: 3 main poles, 1 built-in auxiliary contact, front and side-mounted add-on auxiliary contact blocks - Control circuit: DC operated with solid core magnet circuit. The polarity on the coil terminals (A1+ and A2-) must be respected - Accessories: a wide range of accessories is available. TAL... contactors are fitted with low consumption DC coils and offer a large coil voltage range.

More about TAL16-30-10 77-143V DC Contactor

Technical Specification

MRP (Indian Rupees)

Not for Retail Sale

Enquire Now



Compatibility	TAL Contactors
Max Mechanical Switching Frequency	3600 cycles per hour
Max Electrical Switching Frequency	AC-1 600 cycles per hour, AC-2 / AC-4 300 cycles per hour, AC-3 1200 cycles per hour
Conventional Free-air Thermal Current (Ith)	acc. to IEC 60947-5-1, q = 40 °C 16 ampere, acc. to IEC 60947-4-1, Open Contactors q = 40 °C 30 ampere
Coil Consumption	Holding DC (Umin / Umax) 2.5 / 8.5 watt, Pull-in DC (Umin / Umax) 2.5 / 8.5 watt
Terminal Type	Screw Terminals
Rated Operational Voltage	Auxiliary Circuit 690 volt, Main Circuit 690 volt
Operate Time	Between Coil De-energization and NO Contact Opening 10 ... 17 millisecond, Between Coil Energization and NO Contact Closing 50 ... 100 millisecond
Rated Control Circuit Voltage (Uc)	DC Operation 77-143V
Rated Breaking Capacity AC-3 acc. to IEC 60947-4-1	8 x Ie AC-3
Rated Operational Power AC-3 (Pe)	(220 / 230 / 240 V) 4 KWT, (380 / 400 V) 7.5 KWT, (415 V) 9 KWT, (440 V) 9 KWT, (500 V) 9 KWT, (690 V) 9 KWT
Rated Operational Current DC-13 (Ie)	(125 V) 1.1 / 138 ampere, (24 V) 6 A / 144 watt, (250 V) 0.55 / 138 ampere, (48 V) 2.8 A / 134 watt, (72 V) 2 / 144 ampere
Rated Operational Current AC-3 (Ie)	(220 / 230 / 240 V) 55 °C 17 ampere, (380 / 400 V) 55 °C 17 ampere, (415 V) 55 °C 17 ampere, (440 V) 55 °C 16 ampere, (500 V) 55 °C 14 ampere, (690 V) 55 °C 10 ampere
Rated Operational Current AC-15 (Ie)	(220 / 240 V) 4 ampere, (24 / 127 V) 6 ampere, (380 / 440 V) 3 ampere, (500 V) 2 ampere, (690 V) 2 ampere
Rated Operational Current AC-1 (Ie)	(690 V) 40 °C 30 ampere, (690 V) 55 °C 27 ampere, (690 V) 70 °C 23 ampere
Rated Making Capacity AC-3 acc. to IEC 60947-4-1	10 x Ie AC-3
Rated Frequency Limits	25 ... 400 hertz
Rated Frequency (f)	Supply Circuit 50 60 hertz
Number of Aux Contacts NO	1
Package Width	86 millimetre
Package Length	141 millimetre
Package Height	51 millimetre
Invoice Description	TAL16-30-10 77-143V DC Contactor
Product Range	TAL Contactors
Package Gross Weight	0.52 kilogram
Extended Product Type	TAL16-30-10 77-143V DC
Ambient Air Temperature	Close to Contactor for Storage -60 ... +80 degree Celsius, Close to Contactor without Thermal O/L Relay -40 ... +55 degree Celsius, Close to Contactor Fitted with Thermal O/L Relay -25 ... +55 degree Celsius

Enquire Now



Rated Insulation Voltage (Ui)

acc. to UL/CSA 600 volt, acc. to IEC 60947-4-1 and VDE 0110 (Gr. C) 1000 volt

Product Class

Block Contactors

Total GST Percentage

18.00

HSN Number

85364900

Country of origin

Bulgaria (BG) - Imported by ABB India Limited

[Download](#)



[Offers](#)



[Reviews](#)



Recently Viewed

 <p><u>PUSHBUTTON CP2-10U-02</u> 1SFA619101R1057 Out of Stock</p>	 <p><u>PUSHBUTTON CP4-10L-01</u> 1SFA619103R1044 Out of Stock</p>	 <p><u>PUSHBUTTON CP4-10L-02</u> 1SFA619103R1054 Out of Stock</p>	 <p><u>PUSHBUTTON CP3-10W-02</u> 1SFA619102R1055 Out of Stock</p>
--	--	---	--

Enquire Now

[Write to Us](#)

1800 420 0707

@ contactabb.in@abb.com
(Only for India Inquiries)

Disha - Plot No.5 & 6, 2nd Stage, Peenya
Industrial Area IV, Peenya 560058,
Bangalore, Karnataka, India.

[Facebook](#) [Twitter](#)
 [LinkedIn](#) [Youtube](#)

Copyright © 2025 ABB India Ltd. | Address: Disha - Plot No.5 & 6, 2nd Stage, Peenya Industrial Area IV, Peenya 560058, Bangalore, Karnataka, India.

COMPANY

INFORMATION

PAYMENT METHODS

[About Us](#) [Sell With Us](#) [Our Sellers](#) [Blogs](#) [Exchange and Returns Policy](#) [Privacy Policy](#) [Terms of Use](#) [How to create a Company Account](#) [FAQ](#)

