

[Home](#) > [Electrification](#) > [Automation & Control](#) > [Contactors](#) > [Contactors < 100A](#) > A50-30-00 400-415V 50Hz / 4



♥ [ADD TO WISH LIST](#)

Share with your friends



Automation & Control

# A50-30-00 400-415V 50Hz / 415-440V 60Hz Contactor

Genuine products

Dedicated  
Support

Doorstep Delivery

**₹1983.70** + ₹897.07 (GST 18%)

**eMart**

- 1 +

Buy Now

Add to Cart

Pin Code

Calculate Shipping

Please enter your PIN Code to check the best offers

Product Id#: 1SBL351001R8600

[Be the first to review this product](#)

Sold and delivered by **PIGEON AGENCY**

Enquire Now



A50 contactors are mainly used for controlling 3-phase motors and generally for controlling power circuits up to 690 V AC / 1000 V AC or 220 V DC. The contactors can also be used for many other applications such as isolation, capacitor switching, lighting. The A... series 1-stack 3-pole contactors are of the block type design. - Main poles and auxiliary contact blocks: 3 main poles, front and side-mounted add-on auxiliary contact blocks - Control circuit: AC operated with laminated magnet circuit - Accessories: a wide range of accessories is available.

More about A50-30-00 400-415V 50Hz / 415-440V 60Hz Contactor

Technical Specification

MRP (Indian Rupees)	Not for Retail Sale
Number of Main Contacts NO	3
Compatibility	A Contactors
Max Mechanical Switching Frequency	3600 cycles per hour
Max Electrical Switching Frequency	AC-1 600 cycles per hour, AC-2 / AC-4 150 cycles per hour
Conventional Free-air Thermal Current (Ith)	acc. to IEC 60947-4-1, Open Contactors q 40
Coil Consumption	Average Holding Value 50 / 60 Hz 18 5.5 volt - Value 50 Hz 190 volt - ampere, Average Pull-in ampere
Terminal Type	Screw Terminals
Rated Operational Voltage	Main Circuit 1000 volt
Operate Time	Between Coil De-energization and NO Contact millisecond, Between Coil Energization and NO millisecond
Rated Control Circuit Voltage (Uc)	50 Hz 400-415V; 60 Hz 415-440V
Rated Breaking Capacity AC-3 acc. to IEC 60947-4-1	8 x Ie AC-3
Rated Operational Power AC-6b (Pe)	(230 / 240 V) 40 °C, 50 / 60 Hz 22 KVR, (230 / 240 V) 70 °C, 50 / 60 Hz 20 KVR, 60 Hz 38 KVR, (400 / 415 V) 70 °C, 50 / 60 Hz 38 KVR, (440 V) 40 °C,

Enquire Now

Rated Operational Power AC-3 (Pe)	(220 / 230 / 240 V) 15 KWT, (380 / 400 V) 22 K V) 25 KWT, (500 V) 30 KWT, (690 V) 30 KWT
Rated Operational Current AC-3 (Ie)	(1000 V) 55 °C 23 ampere, (220 / 230 / 240 V) : 400 V) 55 °C 50 ampere, (415 V) 55 °C 50 ampe ampere, (500 V) 55 °C 45 ampere, (690 V) 55 °
Rated Operational Current AC-1 (Ie)	(690 V) 40 °C 100 ampere, (690 V) 55 °C 85 am ampere
Rated Making Capacity AC-3 acc. to IEC 60947-4-1	10 x Ie AC-3
Rated Frequency Limits	25 ... 400 hertz
Package Width	140 millimetre
Package Length	146 millimetre
Package Height	96 millimetre
Invoice Description	A50-30-00 400-415V 50Hz / 415-440V 60Hz C
Product Range	A Contactors
Package Gross Weight	1.16 kilogram
Extended Product Type	A50-30-00 400-415V 50Hz / 415-440V 60Hz
Ambient Air Temperature	Close to Contactor for Storage -60 ... +80 deg Contactor without Thermal O/L Relay (0.85 ... Celsius, Close to Contactor Fitted with Therm degree Celsius, Close to Contactor without T
Rated Insulation Voltage (Ui)	acc. to UL/CSA 600 volt, acc. to IEC 60947-4-1 1000 volt
Product Class	Block Contactors
Total GST Percentage	18.00
HSN Number	85364900
Country of origin	France (FR) - Imported by ABB India Limited

Enquire Now

[Download](#)

[Offers](#)

Reviews

Recently Viewed

 <p><u>A63-30-00 24V 50Hz / 24V 60Hz Contactor</u> 1SBL371001R8100 ₹6,042.00</p>	 <p><u>A75-30-00 24V 50Hz / 24V 60Hz Contactor</u> 1SBL411001R8100 <b>Out of Stock</b></p>	 <p><u>A75-30-00 400-415V 50Hz / 415-440V 60Hz Contactor</u> 1SBL411001R8600 <b>Out of Stock</b></p>	<p><u>A9-</u></p>
---	---	---	-------------------

☐ [Write to Us](#)

1800 420 0707

@ [contactabb.in@abb.com](mailto:contactabb.in@abb.com)  
(Only for India Inquiries)

Disha - Plot No.5 & 6, 2nd Stage, Peenya  
Industrial Area IV, Peenya 560058,  
Bangalore, Karnataka, India.

 [Facebook](#)  [Twitter](#)  
 [Linkedin](#)  [Youtube](#)

Copyright © 2025 ABB India Ltd. | Address: Disha - Plot No.5 & 6, 2nd Stage, Peenya Industrial Area IV, Peenya 560058, Bang

COMPANY	INFORMATION
<a href="#">About Us</a>	<a href="#">Sell Our Products</a>
<a href="#">Our Sellers</a>	<a href="#">Blogs</a>
<a href="#">With Us</a>	<a href="#">Exchange and Returns Policy</a>
	<a href="#">Privacy Policy</a>
	<a href="#">Terms of Use</a>
	<a href="#">How to create a Company Account</a>

Enquire Now

