

# Product data sheet

Specifications

SQUARE D



## MOLDED CASE CIRCUIT BREAKER 600V 80A

FI36080

! Discontinued

### Ordering and shipping details

|                   |                          |
|-------------------|--------------------------|
| Category          | 01020-FI CIRCUIT BREAKER |
| Discount Schedule | DE2                      |
| GTIN              | 00785901132431           |
| Returnability     | No                       |
| Country of origin | MX                       |

### Packing Units

|                              |                         |
|------------------------------|-------------------------|
| Unit Type of Package 1       | PCE                     |
| Number of Units in Package 1 | 1                       |
| Package 1 Weight             | 9.500 lb(US) (4.309 kg) |

### Contractual warranty

|          |           |
|----------|-----------|
| Warranty | 18 months |
|----------|-----------|

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications


Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

|  Materials and Substances |   |
|--|---|
| California proposition 65  | <b>WARNING:</b> This product can expose you to chemicals including: DINP, which is known to the State of California to cause cancer, and DIDP, which is known to the State of California to cause birth defects or other reproductive harm. For more information go to <a href="http://www.P65Warnings.ca.gov">www.P65Warnings.ca.gov</a> |